

AXIS V5925 PTZ Camera

Broadcast-quality HDTV 1080p PTZ camera

AXIS V5925 combines excellent image quality with smooth PTZ control and broadcast-quality audio for professional webcasting. It's compatible with VISCA joysticks and VISCA over IP, making it easy to integrate with your existing AV installations. Offering enhanced security features such as signed firmware and secure boot, it ensures the integrity and authenticity of the firmware. Furthermore, Axis Zipstream with H.264 and H.265 significantly reduces bandwidth and storage requirements without compromising image quality.

- > HDTV 1080p at 60 fps and 30x zoom
- > High-quality audio with XLR inputs
- > VISCA and VISCA over IP support
- > Camstreamer 3-month trial included
- > 3G-SDI and HDMI outputs







AXIS V5925 PTZ Camera

| Progressive scan RGB CMOS 1/2.8" |
|--|
| 4.4–132 mm, F1.4–4.6 |
| Horizontal field of view: 62°–2.3° |
| Vertical field of view: 37°-1.3° Autofocus. P-iris control |
| Automatically removable infrared-cut filter |
| Color: 1.0 lux at 30 IRE F1.4 |
| B/W: 0.03 lux at 30 IRE F1.4 |
| 1/10000 s to 1 s |
| Pan: ±170°, 0.2-100°/s |
| Tilt: -20° - 90°, 0.2-90°/s Zoom: 30x Optical, 12x Digital, Total 360x |
| 256 presets positions, Control queue, On-screen directional |
| indicator, Adjustable zoom speed, PTZ response profiles |
| s (SoC) |
| ARTPEC-7 |
| 1 GB RAM, 512 MB Flash |
| |
| H.264 (MPEG-4 Part 10/AVC) Baseline, Main and High Profiles |
| H.265 (MPEG-H Part 2/HEVC) Main Profile Motion JPEG |
| 1920x1080 HDTV 1080p to 160x90 |
| HDMI/SDI Output: |
| 1080p@50/60 fps (50/60 Hz) |
| Up to 60/50 fps (60/50 Hz) in all resolutions |
| Multiple, individually configurable streams in H.264, H.265 and Motion JPEG |
| Axis Zipstream technology in H.264 and H.265 |
| Controllable frame rate and bandwidth |
| VBR/ABR/MBR H.264/H.265 HDMI |
| HD-SDI: SMPTE 292 |
| 3G-SDI: SMPTE 424 ,SMPTE 425 (3G-SDI mapping supports Level A / Level B dual link mapping) |
| Saturation, brightness, sharpness, white balance, day/night |
| threshold, exposure mode, exposure zones, defogging, rotation: |
| 0°, 180° |
| |
| Two-way, stereo HD-SDI: SMPTE ST 299-1 |
| 3G-SDI: SMPTE ST 299-2 |
| |
| SDI: AES3 24 bit, 48 kHz |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: > 10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced external microphone |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced external microphone Unbalanced line |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced line Line input impedance: >10 kOhm Maximum input level: 2.2 Vrms |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced line Line input impedance: >10 kOhm Maximum input level: 2.2 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: >10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced line Line input impedance: >10 kOhm Maximum input level: 2.2 Vrms |
| SDI: AES3 24 bit, 48 kHz HDMI: LPCM Network: AAC LC 8/16/32/44.1/48 kHz, G.711 PCM 8 kHz, G.726 ADPCM 8 kHz, Opus 8/16/48 kHz, LPCM 48 kHz, Configurable bit rate 2 balanced inputs (left/right) Microphone phantom power 48 V Balanced external microphone Balanced line level Line input impedance: > 10 kOhm Maximum input level: 4.4 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% Signal-to-Noise ratio: > 85 dB @ 0 dB gain, > 78 dB @ 30 dB gain Microphone Power 5 V via 2.2 kOhm Unbalanced line Line input impedance: > 10 kOhm Maximum input level: 2.2 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate |
| |

| SDI output | Output impedance: < 100 Ohm, short circuit proof Maximum output level: > 0.707 Vrms Bandwidth: 20 Hz - 20 kHz (±3 dB), may be limited by sample rate THD+N: < 0.03% @ 10 kOhm load Signal-to-Noise ratio: > 87 dB Bandwidth: 20 Hz - 20 kHz (±3 dB) TUD:NH: = 0.03% |
|---|---|
| | THD+N: < 0.03% Signal-to-Noise ratio: > 87 dB |
| HDMI output | Bandwidth: 20 Hz - 20 kHz (±3 dB) THD+N: < 0.03% Signal-to-Noise ratio: > 87 dB |
| Network | |
| Security | Password protection, IP address filtering, HTTPS ^a encryption, IEEE 802.1x (EAP-TLS) ^a network access control, digest authentication, user access log, centralized certificate management, brute force delay protection, signed firmware, secure boot |
| Supported protocols | IPv4/v6, ICMPv4/ICMPv6, HTTP, HTTP/2, HTTPS ^a , TLS ^a , QoS Layer 3 DiffServ, FTP, CIFS/SMB, SMTP, mDNS (Bonjour), UPnP TM , SNMP v1/v2c/v3 (MIB-II), DNS/DNSv6, DDNS, NTP, RTSP, RTP, SFTP, TCP, UDP, IGMPv1/v2/v3, RTCP, ICMP, DHCPv4/v6, ARP, SOCKS, SSH, SIP, LLDP, CDP, MQTT, Syslog, Link-Local address (ZeroConf), HDMI, 3G-SDI, VISCA |
| System integra | tion |
| Application Programming Interface | Open API for software integration, including VAPIX [®] and AXIS Camera Application Platform; specifications at <i>axis.com</i> One-click cloud connection ONVIF [®] Profile G, ONVIF [®] Profile M, ONVIF [®] Profile S, specification at <i>onvif.org</i> Support for Session Initiation Protocol (SIP) for integration with Voice over IP (VoIP) systems, peer to peer or integrated with SIP/PBX. |
| Event conditions | Analytics, external input, edge storage events, virtual inputs |
| | Audio: audio detection Call: state, state change Device status: above operating temperature, above or below operating temperature, below operating temperature, fan failure, IP address removed, network lost, new IP address, storage failure, system ready, within operating temperature Edge storage: recording ongoing, storage disruption I/0: digital input, manual trigger, virtual input MQIT subscribe PTZ: PTZ malfunctioning, PTZ movement, PTZ preset position reached, PTZ ready Scheduled and recurring: scheduled event Video: average bitrate degradation, live stream open |
| Event actions | MQTT publish Record video: SD card and network share Upload of images or video clips: FTP, SFTP, HTTP, HTTPS, network share and email Pre- and post-alarm video or image buffering for recording or upload Notification: email, HTTP, HTTPS, TCP and SNMP trap PTZ: PTZ preset Overlay text, external output activation, play audio clip, zoom |
| | preset, day/night mode, make call |
| Data streaming | Event data |
| Built-in | Pixel counter, leveling guide |
| installation aids | |
| Analytics | |
| | Included AXIS Video Motion Detection, AXIS PTZ Autotracking Support for AXIS Camera Application Platform enabling installation of third-party applications, see axis.com/acap |
| Analytics | AXIS Video Motion Detection, AXIS PTZ Autotracking Support for AXIS Camera Application Platform enabling |
| Analytics Applications | AXIS Video Motion Detection, AXIS PTZ Autotracking Support for AXIS Camera Application Platform enabling |
| Analytics Applications General | AXIS Video Motion Detection, AXIS PTZ Autotracking Support for AXIS Camera Application Platform enabling installation of third-party applications, see <i>axis.com/acap</i> ASA plastic cover |

| | Terminal block for 2 configurable alarm input/output 3.5 mm stereo mic/line in, 3.5 mm stereo line out XLR-3 (left + right) mic/line in (with 48 V phantom power) HDMI Type A, BNC for SDI DC input RS232 serial connector for VISCA |
|-------------------------|---|
| Storage | Support for microSD/microSDHC/microSDXC card Support for SD card encryption (AES-XTS-Plain64 256bit) Recording to network-attached storage (NAS) For SD card and NAS recommendations see <i>axis.com</i> |
| Operating conditions | 0 °C to 40 °C (32 °F to 104 °F) Humidity 10-85% RH (non-condensing) |
| Storage conditions | -40 °C to 65 °C (-40 °F to 149 °F) Humidity 5 - 95% RH (non-condensing) |
| Approvals | EMC EN 55032 Class A, EN 55035, EN 61000-3-2, EN 61000-3-3, EN 61000-6-1, EN 61000-6-2, FCC Part 15 Subpart B Class A, ICES-3(A)/NMB-3(A), VCCI Class A, RCM AS/NZS CISPR 32 Class A, KC KN32 Class A, KC KN35 Safety IEC/EN/UL 62368-1, CAN/CSA C22.2 No. 62368-1, KC-Mark, IS 13252 Environment IEC 60068-2-1, IEC 60068-2-2, IEC 60068-2-6, IEC 60068-2-14, IEC 60068-2-27, IEC 60068-2-78 |

| | Network NIST SP500-267 |
|-------------------------|--|
| Dimensions | Height: 180 mm (7.1 in) ø 136 mm (5.4 in) |
| Weight | 1.5 kg (3.3 lb) |
| Included accessories | Power supply, wall/ceiling mount, terminal connector for I/O, installation guide, Windows [®] decoder user license, Camstreamer 3-month trial |
| Optional accessories | AXIS T8310 Video Surveillance Control Board AXIS VISCA Cable For more accessories, see <i>axis.com</i> |
| Languages | English, German, French, Spanish, Italian, Russian, Simplified Chinese, Japanese, Korean, Portuguese, Traditional Chinese |
| Warranty | 5-year warranty, see axis.com/warranty |

a. This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit. (openssl.org), and cryptographic software written by Eric Young (eay@cryptsoft.com).

Environmental responsibility:

axis.com/environmental-responsibility

